

| Type of environment and/or equipment | Interval between inspection and tests | | | | |
|--|--|---|-----------|-------------------------------------|-----------|
| | Equipment including Class I equipment, Class II equipment, cord sets, cord extension sets and EPODs | Residual current devices (RCDs) | | | |
| | | Push-button test – by user | | Operating time and push-button test | |
| (a) | (b) | Portable (c) | Fixed (d) | Portable (e) | Fixed (f) |
| 1. Factories, workshops, places of manufacture, assembly, maintenance or fabrication | 6 months | Daily, or before every use, whichever is the longer | 6 months | 12 months | 12 months |
| 2. Environment where the equipment or supply flexible cord is subject to flexing in normal use OR is open to abuse OR is in a hostile environment | 12 months | 3 months | 6 months | 12 months | 12 months |
| 3. Environment where the equipment or supply cord is NOT subject to flexing in normal use and is NOT open to abuse and is NOT in a hostile environment | 5 years | 3 months | 6 months | 2 years | 2 years |
| 4. Residential type areas of: hotels, residential institutions, motels, boarding houses, halls, hostels accommodation houses, and the like | 2 years | 6 months | 6 months | 2 years | 2 years |
| 5. Equipment used for commercial cleaning | 6 months | Daily, or before every use, whichever is the longer | N/A | 6 months | N/A |
| 6. Hire equipment: Inspection | Prior to hire | Including push-button test by hirer prior to hire | | N/A | N/A |
| Test and tag | 3 months | N/A | | 3 months | 12 months |
| 7. Repaired, services and second-hand equipment | After repair or service which could affect electrical safety, or on reintroduction to service, refer to AS/NZS 5762. | | | | |